

### SMALL AND SIMPLE...


- 1100W continuous / 2200W peak power
- LCD display - Volt/Watt/Battery Level
- Ultra silent (thermal fan)
- 2 x standard North American AC outlets
- 2 x USB charging ports 2.1A (shared)
- Tablet charging compatible from USB ports
- 3 Ft. battery cables included
- ON / OFF Remote Control (optional)

### WORKS WITH...

- Hand Held Power Tools
- Televisions
- Gaming Consoles
- Home Electronics
- Small Appliances
- and more...

## EN1100

1100W Power Inverter - Get power on the GO!  
This heavy duty Power Inverter connects directly to a 12 Volt DC battery to power hand held power tools, televisions, gaming consoles, home electronics and small appliances in your vehicle. This unit also features an LCD display, which shows the output wattage or input voltage and battery level. With this inverter, you will never be left without power when you need it!



**Before Using Your Power Inverter:**  
Please read all instructions and cautionary markings on the package and manual

### Product Detail:

**Designation:** 1100 Watt POWER INVERTER

**Model:** EN1100

**Color:** Black

**AC output voltage:** 120VAC/60Hz

**Continuous AC output power:** 1100W

**Peak output power:** 2200W

**AC output wave form:** Modified sine wave

**AC output frequency:** 60 ± 3Hz

**2 x USB DC output current:** 2.1 Amp (Shared)

**Typical Weight (lbs):** 3.16 lbs

**Dimensions (in):** 2.72(H) x 10.98(L) x 5.59(W)

#### **Important Notice**

This datasheet contains information specific to products manufactured at the time of its publication  
**Contents herein do not constitute a warranty**  
©Energizer / All Rights Reserved